



### C-Warm Strobe Lighting

Model: LD102-A2W Str

Item: SC3909

Firmware: S1.03

LCD Menu:

Main Menu	Function	Value	Note
AUTO	AU01	N/A	Automatic Mode Function 1 <sup>st</sup>
	AU02	N/A	Automatic Mode Function 2 <sup>nd</sup>
DMX	DMX-512 Address	1-512	Setup DMX-512 Address

DMX-512 Channels:

Channel 1	0-8	OFF
	9-214	Strobe Slow -> Fast
	215-255	Random Strobe
Channel 2	0-255	Brightness For Cool White 6000K
Channel 3	0-255	Brightness For Amber
Channel 4	0-255	Brightness For Warm White 3200K
Channel 5	0-50	No Function (Color Control By Ch2-Ch4)
	51-101	Color Jumping Function 1
	102-152	Color Jumping Function 2
	153-203	Color Jumping Function 3
	204-255	Color Jumping Function 4
Channel 6	0-255	Color Jumping Speed Fast -> Slow

SUPER-CAN Industry Growing Co., LTD

<http://www.supercan.cn>